General Description

The Maxim MXL1016 (10ns, typ) high-speed, complementary-output comparator is designed specifically to interface directly to TTL logic while operating from either a dual ±5V supply or a single +5V supply.

The MXL1016 remains stable with the outputs in the active region, which greatly reduces output instability common with slow-moving input signals. In addition, an output latch (LE) is provided.

For lower-power, higher-performance comparators, see the MAX912/MAX913 dual/single comparators data sheet. The MAX913 is an improved plug-in replacement for the MXL1016 and the MAX912 is the dual equivalent to the MAX913.

_Features

- Ultra Fast (10ns, typ)
- Single +5V or Dual ±5V Supply Operation
- Complementary TTL Outputs
- Low Offset Voltage: 1mV
- ♦ No Minimum Input Slew-Rate Requirement
- No Power-Supply Current Spiking
- Output Latch

NAME

V+

IN+

IN-

V-

LE

GND

QOUT

QOUT

PIN

1

2

З

Δ

5

6

7

8

Ordering Information

Pin Description

FUNCTION

Negative Power Supply, -5V for dual supply

Latch Enable. QOUT and QOUT are

Positive Power Supply +5V

or GND for single supply

latched when LE is high

Complementary TTL Output

Noninverting Input

Inverting Input

Ground

TTL Output

PART	TEMP RANGE	PIN-PACKAGE
MXL1016CN8	0°C to +70°C	8 Plastic DIP
MXL1016CS8	0°C to +70°C	8 SO

- High-Speed A/D Converters Zero-Crossing Detectors
 - Current Sense for Switching Regulators
 - High-Speed Sampling Circuits
 - High-Speed Triggers
 - Line Receivers
 - Extended Range V/F Converters
 - Fast Pulse Height/Width Discriminators



Pin Configuration

Applications

M/IXI/M

Maxim Integrated Products 1

For pricing, delivery, and ordering information, please contact Maxim/Dallas Direct! at 1-888-629-4642, or visit Maxim's website at www.maxim-ic.com.

ABSOLUTE MAXIMUM RATINGS

Positive Supply Voltage	7V
Negative Supply Voltage	7V
V+ to V	
Differential Input Voltage	
MXL1016	±5V
Input Voltage (either input)	
MXL1016	Equal to Supplies
Latch Pin Voltage	Equal to Supplies

Output Current (continuous)±20mA
Continuous Power Dissipation ($T_A = +70^{\circ}C$)
8-Pin Plastic DIP (derate 9.09mW/°C above +70°C)727mW
8-Pin SO (derate 5.88mW/°C above +70°C)471mW
Operating Temperature Ranges:
MXL10160°C to +70°C
Storage Temperature Range65°C to +150°C
Lead Temperature (soldering, 10s)+300°C

Stresses beyond those listed under "Absolute Maximum Ratings" may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated in the operational sections of the specifications is not implied. Exposure to absolute maximum rating conditions for extended periods may affect device reliability.

ELECTRICAL CHARACTERISTICS

(V+ = 5V, V- = -5V, V_{OUT}(Q) = 1.4V, V_{LE} = 0V, T_A = T_{MIN} to T_{MAX}, unless otherwise noted. Typical values are at T_A = +25°C.) (Note 1)

PARAMETER	SYMBOL	CONDITIONS		MIN	ТҮР	МАХ	UNITS
Input Offset Voltage (Note 2)	V _{OS}	$R_{S} \le 100\Omega$	$T_A = +25^{\circ}C$		1.0	±3	mV
			$T_A = T_{MIN}$ to T_{MAX}			3.5	
Input Offset-Voltage Drift	$\Delta V_{OS} / \Delta T$	$T_A = T_{MIN}$ to T_{MAX}			4		µV/°C
Input Offset Current (Note 2)	I _{OS}	$T_A = +25^{\circ}C$			0.3	1	μA
		$T_A = T_{MIN}$ to T_{MAX}				1.3	
Input Bias Current (Note 3)	IB	$T_A = +25^{\circ}C$			5	10	μA
		$T_A = T_{MIN}$ to T_{MAX}				13	
Input Voltage Range	V _{CM}	Dual +5V and -5V supply		-3.75		+3.50	V
		Single 5V supply		+1.25		+3.50	
Common-Mode Rejection Ratio	CMRR	$-3.75V \le V_{CM} \le 3.5V$		80	96		dB
Power-Supply Rejection Ratio	PSRR	Positive supply: $4.6V \le V + \le 5.4V$		60	75		dB
		Negative supply: $-2V \ge V- \ge -7V$		80	100		
Small-Signal Voltage Gain	Av	$1V \le V_{OUT} \le 2V$, $T_A = +25^{\circ}C$		1400	3000		V/V
Output High Voltage	V _{OH}	V+ ≥ 4.6V	I _{OUT} = 1mA	2.7	3.4		N/
			I _{OUT} = 10mA	2.4	3.0		V
Output Low Voltage	V _{OL}	I _{SINK} = 4mA			0.3	0.5	- V
		$I_{SINK} = 10$ mA, $T_A = +25$ °C			0.4		
Positive Supply Current	l+	(Note 4)			25	35	mA
Negative Supply Current	-	(Note 4)			3	5	mA

ELECTRICAL CHARACTERISTICS (continued)

 $(V + = 5V, V - = -5V, V_{OUT}(Q) = 1.4V, V_{LE} = 0V, T_A = T_{MIN}$ to T_{MAX} , unless otherwise noted. Typical values are at $T_A = +25^{\circ}C$.) (Note 1)

PARAMETER	SYMBOL	CONDITIONS		MIN	ТҮР	МАХ	UNITS
Latch Pin High Input Voltage	VIH			2.0			V
Latch Pin Low Input Voltage	VIL					0.8	V
Latch Pin Current	١ _١ ٢	$V_{LE} = 0V$				-500	μA
Propagation Delay (Note 5)	tpD	$\Delta V_{IN} = 100 mV,$ OD = 5mV	$T_A = +25^{\circ}C$		10	14	ns
						16	
		$\Delta V_{IN} = 100 mV,$ OD = 20mV	$T_A = +25^{\circ}C$		9	12	
						15	
Differential Propagation Delay (Note 5)	ΔtpD	$\Delta V_{IN} = 100 \text{mV}, \text{OD} = 5 \text{mV}, \text{T}_{A} = +25^{\circ}\text{C}$				4	ns
Latch Setup Time	ts∪	(Note 6)			2		ns
Latch Hold Time	t _H	(Note 6)			2		ns

Note 1: All specifications are 100% tested at T_A = +25°C, unless otherwise noted. Specification limits over temperature (T_A = T_{MIN} to T_{MAX}) are guaranteed by design.

Note 2: Input offset voltage is defined as the average of the two input offset voltages, measured by forcing first one output, then the other to 1.4V. Input offset current is defined in the same way.

Note 3: Input bias current (IB) is defined as the average of the two input currents.

Note 4: Supply currents are measured with VOUT (Q) driven to both VOH and VOL (not 1.4V).

Note 5: t_{PD} and Δt_{PD} cannot be measured in automatic handling equipment with low values of overdrive. Characterization and correlation tests have shown that t_{PD} and Δt_{PD} limits can be guaranteed by design. Electrical Characteristic DC tests are performed to guarantee that all internal bias conditions are correct. For low overdrive conditions, V_{OS} is added to overdrive.

Note 6: Input latch setup time, t_{SU}, is the interval in which the input signal must be stable prior to asserting the latch signal. The hold time, t_H, is the interval after the latch is asserted in which the input signal must be stable.

Package Information

(The package drawing(s) in this data sheet may not reflect the most current specifications. For the latest package outline information, go to **www.maxim-ic.com/packages**.)



///XI//

Package Information (continued)

(The package drawing(s) in this data sheet may not reflect the most current specifications. For the latest package outline information, go to <u>www.maxim-ic.com/packages</u>.)



Maxim cannot assume responsibility for use of any circuitry other than circuitry entirely embodied in a Maxim product. No circuit patent licenses are implied. Maxim reserves the right to change the circuitry and specifications without notice at any time.

Maxim Integrated Products, 120 San Gabriel Drive, Sunnyvale, CA 94086 408-737-7600 _

© 2003 Maxim Integrated Products Printed USA MAXIM is a registered trademark of Maxim Integrated Products.

5